


BTR5000 Waveform Cable fault locator

USB type Adapter

Innovative performance for all level technician •



STREADE

IP68 grade against tough condition •

Real intuitive GUI & UX for smart work

Available power bank battery ° 888 08

7" Large scale Color LCD (800*480) •--

Unified port for communication & recharge •

Superb accuracy & resolution •-----

• The real cable fault locator, BTR5000 delivers all the innovative and sensational performances that all cable technicians have been requesting for in a Cable installation & maintenance.

• Born to measure all type of metallic cable fault

Measurement

- Pulse : 3ns ~ 10µs
- \bullet Accuracy : \pm 0.1 % of reading
- \pm 0.1m for coaxial
- Resolution : 2.5cm

User friendly

- Familiar with smart device interface.
- Easy to start, Fun for work.

Smart

• Support USB connector for recharge & telecommunication

Multi use

Easy report & Sharp waveform analysis

• Variety of the cable environments (Power, Electric, Telecom, Transportation, Environmental, ETC)

Support WAVE MATE™

Smart capture function

We, BECS have been researching many of the difficult issues reported in the cable management industry for many years. Since then we have started again at the base for real cable fault locator to real user.

BECS waveform Cable fault locator (Model No.: BTR5000) is a high-end instrument capable of identifying a wide range of cable faults using Time Domain Reflectometry, designed to meet today's most demanding network cabling problems. With high accuracy as well as user-friendly features, BECS waveform Cable fault locator is an excellent instrument for all cable management industry.

3Fl, 20, Kkachisan-ro, Gangseo-gu, Seoul, Korea 07726. Tel. +82 2 6274 0554 Fax. +82 2 6294 0554 E-mail. sales@becscorp.co.kr http://www.becscorp.co.kr





3TR5000


Waveform Cable fault locator

Performance	Range	50cm ~ 20,000m for coaxial cable
	Resolution	2.5cm
	Accuracy	\pm 0.1 % of reading \pm 0.1m for coaxial
	V.O.P setting	10.0 ~ 99.9 % (in 0.1% step)
	Pulse width	3, 6, 12, 25, 50, 100, 200, 500ns, 1,2,5,10µs
	Display	7inch, 800 * 480 TFT color LCD
	Output impedance	50, 75Ω
Interface	Internal memory	8GB
	Connector	BNC Female
	Refresh rate	5 times per second
	Communication port	USB A
	Internal battery	3.7V Li-ion battery pack, 10,000mAh
	Adaptor	USB A
Power	Operation time	Approx. 6 hours
	Operation temp	-10 °C ~ +60°C
	Storage temp	-30 °C ~ +80 °C
Environment	Humidity	Less 95%
	Size	W:300mm * D:249mm * H: 119mm
	Weight	Less 2.5kg
	Warranty	1 year from date of purchase

% Specifications subject to change without notice.

| Application

BECS Waveform Cable Fault Locator (Model No.: BTR5000) has been using in many industrial sites.





3Fl, 20, Kkachisan-ro, Gangseo-gu, Seoul, Korea 07726. Tel. +82 2 6274 0554 Fax. +82 2 6294 0554

E-mail.sales@becscorp.co.kr http://www.becscorp.co.kr